

Cấu hình Wifi modem CIG G-97D2

- Nhập địa chỉ: <http://192.168.1.1>
- Account mặc định: xem dưới đây modem hoặc gọi lên tổng đài FPT Telecom
- Vào Wireless Setup

1. Tắt/ bật chức năng Wifi

Chọn mục Basic

The screenshot displays the 'Basic' configuration page for the 2.4G Radio. The left sidebar shows the navigation menu with 'Basic' selected. The main content area contains the following settings:

- 1. Set wireless radio state.**
2.4G Radio: ☒ Enable ☐ Disable
- 2. Select 802.11 mode.**
802.11 Mode: Auto(802.11b/g/n)
- 3. Select channel bandwidth.**
Channel Bandwidth: 20M
- 4. Select channel.**
Channel: Auto Selection
- 5. Select wireless power level.**
Wireless Power Level: 100%
- 6. Set max client number.**
Max Client Number: 0
- 7. Click "Apply" to save your settings.**
Apply

Red annotations on the image include:

- A red box around the '2.4G Radio' section with the text: **Chọn Enable/Disable để bật/tắt WiFi**
- A red box around the settings for 802.11 Mode, Channel Bandwidth, Channel, and Wireless Power Level with the text: **Để mặc định**
- A red box around the 'Apply' button with the text: **Bấm Apply để lưu cấu hình**

2. Đổi tên sóng wifi

Chọn tiếp mục SSID và làm theo hướng dẫn như hình

The screenshot shows the 'SSID' configuration page in a router's web interface. The page has a top navigation bar with icons for Gateway Status, Wireless Setup, Advanced Setup, Security Setup, Utilities, and Support Console. On the left, there is a sidebar with '2.4G Radio' selected, and sub-menus for Basic, SSID, Wireless Security, Advanced, WPS, and Access Control. The main content area is titled 'SSID' and includes the instruction 'Select and configure wireless networks.'.

The configuration steps are as follows:

- 1. Select SSID to configure.** A dropdown menu shows 'SSID 1' selected. A red box highlights this section with the annotation 'Để mặc định' (Leave default).
- 2. Set SSID state.** The 'SSID State' is set to 'Enable' (radio button selected). A red box highlights this section with the annotation 'Để mặc định'.
- 3. Enter a SSID name.** The 'SSID Name' field contains 'FPT Telecom-6736'. A red box highlights this section with the annotation 'Tên mạng WiFi' (WiFi network name).
- 4. Set SSID broadcast state.** The 'SSID Broadcast State' is set to 'Broadcast SSID' (radio button selected). A red box highlights this section with the annotation 'Để mặc định'.
- 5. Set station isolation in BSS.** The 'Station Isolation' is set to 'Disable' (radio button selected). A red box highlights this section.
- 6. Click "Apply" to save your settings.** A red box highlights the 'Apply' button with the annotation 'Bấm Apply để lưu cấu hình' (Click Apply to save configuration).

3. Đổi mật khẩu wifi

Chọn mục Wireless Security và làm theo hướng dẫn như hình.

Lưu ý: nhập mật khẩu từ 8 ký tự trở lên, có phân biệt chữ hoa chữ thường.

Gateway Status

Wireless Setup

Advanced Setup

Security Setup

Utilities

Support Console

2.4G Radio

Basic

SSID

Wireless Security

Advanced

WPS

Access Control

Wireless Security

Configure wireless security options for each network.

1. Select SSID to configure.

SSID

SSID 1

2. Select security type.

Security Type

WPA/WPA2-Personal

3. Select encryption type.

Encryption Type

TKIP/AES

4. Enter security passphrase.

Security Passphrase

f2553714

5. Click "Apply" to save your settings.

Apply

Để mặc định

Nhập Password mạng WiFi

Bấm Apply để lưu cấu hình